



### **Foreword**

Please note: this document is a draft version of the test guidance based on the principles previously communicated. As the principles have not yet been finalised, the content in this document may change.

This document aims to provide guidance to Dynamic Containment providers to National Grid. This document covers the testing requirements for pre-qualification assessment and reproving of this service. The tests outlined in the document are to verify that the requirements of the service specified in contract documents can be met. For any further enquires or questions, contact your Account Manager or:

E-mail <u>commercial.operation@nationalgrideso.com</u>

Telephone +44 (0) 1926 654611

The test results will be assessed by an Independent Technical Expert (ITE). (See Appendix A)

To complete the pre-qualification requirement, the following information must be submitted to National Grid Electricity System Operator (NGESO):

- The test data, in the format outlined in Appendix C
- A report from the ITE, in the format outlined in Appendix E
- A CV, setting out the qualifications and experience of the ITE



## **Contents**

Foreword	1
Contents	2
Test Requirements	3
Service description	4
Dynamic Containment Test Requirements	5
Test 1 – Step Test	5
Test 2 – Frequency Sweep Test	9
Test 3 Duration Test	
Test 4 – Live System Frequency Response Test  Pass Criteria for Test 4	
Appendices	15
Appendix A - Independent Technical Expert (ITE)	16
Appendix B – Test Signals	17
Appendix C - Dynamic Test Data Format	18
Appendix D – Dynamic Test Assessment	19
Appendix E- Dynamic Test Certificate Template	20



**Test Requirements** 




### **Service description**

Dynamic Containment is a fast-acting frequency response service to contain frequency within the statutory range of +/-0.5Hz in the event of a sudden demand or generation loss. The service delivers very quickly and proportionally to frequency deviation.

**Table 1- Dynamic Containment Service Specification** 

Service specification	Details
Deadband delivery	0% (+/- 0.015Hz)
Small linear delivery	Between 0.015Hz and 0.2Hz (maximum of 5% at 0.2Hz)
Knee point activation	+/- 0.2Hz is 5%
Full delivery	+/- 0.5Hz is 100%
Linear delivery knee point	0.2Hz
Full activation	0.5Hz
Full delivery	1s (but no faster than 0.5s)

Figure 1 – Dynamic Containment Delivery Requirements





### **Dynamic Containment Test Requirements**

The Dynamic Containment tests assess the capability of the service provider to deliver dynamic response in accordance with the balancing service contract.

Tests 1, 2 and 3 assess response against injected frequency profiles. Test 4 assesses response whilst connected to live system frequency. The frequency profile can be injected either at site or remotely. The minimum sample rate for all tests is 20Hz. See Appendix B for information on test signals.

### Test 1 – Step Test

The purpose of Test 1 is to assess the unit's ability to deliver the required response at discreet frequency deviations.

- The frequency injections to be used are shown in Figure 2 and Table 2 below.
- Each step is sustained for 180 seconds to verify the response.
- The frequency will then be returned to 50Hz for a minimum of 30 seconds, or until the output is stable, before the next injection is applied.
- Tests 1.1 and 1.2 are designed to ensure that the unit does not provide any response within the deadband.
- The minimum sample rate for Tests 1 is 20Hz.

### Pass Criteria for Test 1

- The minimum of the sampled values of active power response within each 3 minute timescale falls within tolerances shown in **Table 3** and shown graphically in **Figure 3**.
- Delivery of full response of active power due to a change in frequency is as per Figure 4.
- The Unit should monotonically progress to its required response.
- The standard deviation of load error at steady state over a 3-minute period must not exceed 2.5% of the expected active power response.

Figure 2 - Test 1




Table 2 - Test 1 Frequency Injection Profile corresponding with times


Test	Parameter			,	Values		
	Time /s	0	30	30	210	210	240
1.1	Frequency /Hz	50	50	50.01	50.01	50	50
1.2	Frequency /Hz	50	50	49.99	49.99	50	50
1.3	Frequency /Hz	50	50	50.02	50.02	50	50
1.4	Frequency /Hz	50	50	49.98	49.98	50	50
1.5	Frequency /Hz	50	50	50.1	50.1	50	50
1.6	Frequency /Hz	50	50	49.9	49.9	50	50
1.7	Frequency /Hz	50	50	50.2	50.2	50	50
1.8	Frequency /Hz	50	50	49.8	49.8	50	50
1.9	Frequency /Hz	50	50	50.3	50.3	50	50
1.10	Frequency /Hz	50	50	49.7	49.7	50	50
1.11	Frequency /Hz	50	50	50.4	50.4	50	50
1.12	Frequency /Hz	50	50	49.6	49.6	50	50
1.13	Frequency /Hz	50	50	50.5	50.5	50	50
1.14	Frequency /Hz	50	50	49.5	49.5	50	50



Table 3 - Test 1 Frequency Injection and expected response value

Test Number	Frequency Step	Expected Response	Allowable Power Tolerance
1.1	50.01	0%	n/a
1.2	49.99	0%	n/a
1.3	50.02	0.135%	+2.5%/-0.135%
1.4	49.98	0.135%	+2.5%-0.135%
1.5	50.1	2%	+2.5%/-2%.
1.6	49.9	2%	+2.5%/-2%
1.7	50.2	5%	+/- 2.5%.
1.8	49.8	5%	+/- 2.5%.
1.9	50.3	37%	+/- 2.5%.
1.10	49.7	37%	+/- 2.5%.
1.11	50.4	68%	+/- 2.5%.
1.12	49.6	68%	+/- 2.5%.
1.13	50.5	100%	+/- 2.5%.
1.14	49.5	100%	+/- 2.5%.

Figure 3 Graphical representation of tolerance bands for the expected response at different frequencies – sample chart only



Min ramp rate  $\mathsf{RR}_{\mathsf{min}}$ 0.5 s 1.0 s  $T_{dmin}$  $T_{\text{dmax}}$ Required delivery quantity  $R_x$ 1.0 s  $T_0$ 0.25 s 0.5 s  $T_{imin}$  $T_{imax}$ Max ramp rate  $RR_{max}$ 

Figure 4 – Graphical representation of timescales in which response should be delivered



### **Test 2 – Frequency Sweep Test**


Test 2 assesses the unit's performance against a varying frequency over the entire performance envelope.

- The frequency injections to be used are shown in Figures 5 and 6 and Table 4 below.
- The minimum sample rate for Tests 2.1 and 2.2 is 20Hz.


### Pass Criteria for Tests 2.1 and 2.2

- Delay in response following a change in frequency should be ≥0.25s and ≤0.5s.
- For Test 2.1 and 2.2, active power response is within the tolerances in Figure 7/Figure 8 and
- Table 5









**Table 4 - Test 2 Frequency Injection Profiles** 

Time /s	Injected Fr	equency /Hz
Time /s	<b>Test 2.1</b>	<b>Test 2.2</b>
0	50	50
30	50	50
30	49.4	50.6
60	49.4	50.6
65	49.6	50.4
70	49.8	50.2
75	50	50
80	50.2	49.8
85	50.4	49.6
90	50.6	49.4
120	50.6	49.4
120	50	50
150	50	50

Figure 7 - Test 2.1b Tolerance - sample




Figure 8 - Test 2.2b Tolerance - sample





Table 5 - Test 2.1b and 2.2b Sweep Test tolerances

	Test	2.1b	Test	2.2b
	<b>Negative Active</b>	<b>Power Gradient</b>	Positive Active I	Power Gradient
Time/s	Expected Percentage Active Power Response/%	Tolerance	Expected Percentage Active Power Response/%	Tolerance
62.5	100.0	TBC	-100.0	TBC
64.5	74.7	TBC	-74.7	TBC
65	68.3	TBC	-68.3	TBC
67.5	36.7	TBC	-36.7	TBC
70	5.0	TBC	-5.0	TBC
72.5	2.3	TBC	-2.3	TBC
75	0.0	TBC	0.0	TBC
77.5	-2.3	TBC	2.3	TBC
80	-5.0	TBC	5.0	TBC
82.5	-36.7	TBC	36.7	TBC
85	-68.3	TBC	68.3	TBC
87.5	-100.0	TBC	100.0	TBC
89.5	-100.0	TBC	100.0	TBC

### **Test 3 Duration Test**


Test 3 assesses the unit's ability to sustain full response for 15 minutes.

- Operation will be tested at ±100% of capability to ensure the system is compliant.
- This is carried out by a frequency step of ±0.6Hz onto the system for 15 minutes.
- The frequency injection profiles are shown in Figures 9 and 10 and Tables 6 and 7.

### Pass criteria for test 3:

- The standard deviation of load error at steady state over a 900 second period must not exceed 2.5% of the maximum contracted active power.
- Sustain response for 15 minutes.

**Figure 9 Test 3.1 Injection Profile** 



**Figure 10 Test 3.2 Injection Profile** 






Table 6: Test 3.1 Frequency Injection Table Corresponding with times

	Test 3.1 Frequency injection table					
Time /s	0	30	30	930	930	960
Frequency /Hz	50	50	50.6	50.6	50	50

Table 7: Test 3.2 Frequency Injection Table Corresponding with times

	Test 3.2 Frequency injection table					
Time /s	0	30	30	930	930	960
Frequency /Hz	50	50	49.4	49.4	50	50


### Test 4 – Live System Frequency Response Test

Test 4 assesses the unit's response to system frequency in a live environment. The minimum sample rate for this test is 20Hz and duration is 15 minutes where system frequency and active power response will be recorded. As part of test 4, you are required to provide evidence that the protection settings are in line with the grid code (+/- of 5% of 50Hz).

### Pass Criteria for Test 4

- Provide an active power response consistent with the contracted performance within timescales.
- Provide evidence protection setting comply with grid code.

Figure 11 - Sample System Frequency





## **Appendices**



# Appendix A - Independent Technical Expert (ITE)

The Dynamic Containment test results will be assessed by an **Independent Technical Expert** (ITE) who will prepare a **Test Certificate**. The following definitions shall apply:

**Group** means, for any person, another person who is the direct or indirect **Holding Company** of that person and any **Subsidiary** of that **Holding Company**.

**Holding Company** means, in relation to a company, any other company in respect of which it is a **Subsidiary**.

**Independent Technical Expert** means an experienced technical expert with expertise in the operation of demand side response (DSR) or generating units or electricity Interconnectors (as the case may be), **Independent** of the prospective response provider, engaged by the prospective response provider at its expense to carry out a technical assessment and prepare a **Test Certificate.** 

**Independent** means, for any technical expert and the applicable prospective response provider, that the technical expert is:

- (a) not in the same **Group** as the prospective response provider; and
- (b) neither engaged on terms, nor party to any other arrangements, which could allow the prospective response provider or any member of its **Group** to exercise undue influence on any assessment of the **Test Certificate** prepared by that technical expert or otherwise compromise the objectivity of any such assessment and test certificate to the **Required Technical Standard**.

Required Technical Standard means, with respect to any assessment and Test Certificate prepared by an Independent Technical Expert that:

- (a) to the best of the **Independent Technical Expert**'s knowledge and belief all information provided in it is accurate, complete and not misleading; and
- (b) any opinions or forecasts in the assessment have been conservatively prepared on assumptions which it considers to be fair and reasonable.

**Subsidiary** means a subsidiary within the meaning of section 1159 of the Companies Act 2006 (but relation to an Interconnector, or shareholder in such provider, subsection (1)(a) of that section shall apply as if a "majority of the voting rights" included 50% only of those rights)

**Test Certificate** means a certificate in the form set out in Appendix E (dynamic) prepared by an **Independent Technical Expert**.



## Appendix B – Test Signals

The limits of error and minimum sample rates for testing are shown below in **Table 8**. All success criteria are subject to the stated limit of error/accuracy threshold.

Table 8 - Limits of error and minimum sample rates for Dynamic Service Testing

	Limit of error/ Accuracy threshold	Minimum Sample rate Test 1	Minimum Sample rate Tests 2 and 3
Frequency (Hz)	±0.01 Hz	20Hz	20Hz
Active Power (MW)	Please see pass criteria	20Hz	20Hz

Simulations / simulated tests are not permitted. Each test submitted must record real time data from the plant and sites under test: The test data submitted must come from the specific site to be contracted; substituted data will not be accepted. Test results much not be changed before submission for analysis.

### **Test Signals**

In ALL cases, the data should record ALL required signals for at least 30 seconds BEFORE the application of the frequency injection signal and for at least 30 seconds AFTER the completion of the test.

For ALL services, the data for the following signals will need to be provided

- a) Time
- b) Active Power
- c) System Frequency or Injected frequency as appropriate
- d) Any other relevant signals that may affect the success criteria such as Relay Logic for non-dynamic.



# **Appendix C - Dynamic Containment Test Data Format**

Figure 12 - Sample Dynamic Test Data Format

Provider	Company Name	
Date	xx-xx-xxxx	
Test	1	
Service	Dynamic FFR PSH	
Location	AA	
Site/Group/Plant	A	
Time	Injected Frequency (Hz)	Measured Power (MW)
0	50.000	0.000
0.1	50.000	0.000
0.2	50.000	0.000
0.3	50.000	0.000
0.4	50.000	0.000
0.5	50.000	0.000
0.6	50.000	0.000
0.7	50.000	0.000
0.8	50.000	0.000
0.9	50.000	0.000
1	50.000	0.000
1.1	50.000	0.000
1.2	50.000	0.000
1.3	50.000	0.000
1.4	50.000	0.000
1.5	50.000	0.000
1.6	50.000	0.000

Further columns can be added to include data for several sites if required.

For Test 4 replace 'Injected Frequency' with 'Measured Frequency'.



# **Appendix D – Dynamic Containment Test Assessment**

Excel Analysis Tool published with User Guide. (Not available)

See Test certificate template in Appendix E for further guidance.



# **Appendix E – Dynamic Test Certificate Template**

Please use this Test Certificate format and submit to NGESO, along with the test data and CV of the ITE employed by the prospective response provider.

### Prospective Response Provider Company Details

Contracted company name	
Primary contact name	
Contact number/s	
Email address	

### **Contract Details**

Contract Details		
Contract ID		
Service type, e.g. Static or Dynamic		
Asset type, e.g. diesel generator, battery etc		
Unit make up, e.g. single or aggregated	Describe here what is included in this test e.g.  Single asset, group of assets, asset/s being assessed within an existing Unit.	
Aggregation methodology (if appropriate)		
Unit location / ID		
Contract signed date		
Service start date		
Test date		

### Dynamic Service Details (example here is for a 5MW Unit)

Deadband	±0.015Hz
Response / MW	5



### **Test Results**

Further relevant test description/commentary here

Table 1 – Contracted vs Actual Response Values

Frequency		Primary / MW	
Deviation			
/Hz	Tolerance	Contracted	Actual
-0.5	TBC	5.0	5.0
-0.4	TBC	3.4	3.4
-0.3	TBC	1.8	1.8
-0.2	TBC	0.3	0.3
-0.1	TBC	0.1	0.1
-0.01	TBC	0.0	0.0
0	TBC	0.0	0.0
0.01	TBC	0.0	0.0
0.1	TBC	-0.1	-0.1
0.2	TBC	-0.3	-0.3
0.3	TBC	-1.8	-1.8
0.4	TBC	-3.4	-3.4
0.5		-5.0	-5.0

Test	Pass Criteria	Pass/Fail	Comment
1	Minimum of the sampled values of active power response within each 3 minute timescale fall within tolerances	Pass	Note result here (See Figure)
1	Delivery of active power due to a change in frequency is between 0.5-1s	Pass	Note result here.
1	•The Unit should monotonically progress to its required response	Pass	Refer to figures below
1	The standard deviation of load error at steady state over a 3 minute period must not exceed 2.5% of the expected active power response	Pass	Standard deviation is assessed from 10 seconds until 3 minutes after the frequency step.
2.1a 2.2a	A noticeable change in power in the correct direction is observed and is equal to the total maximum contracted value.	Pass	
2.1b 2.2b	Active power response is within the allowed tolerances.	Pass	Show in figure below with tolerance bands overlaid.



Test	Pass Criteria	Pass/Fail	Comment
3	Response is sustained for 15 minutes	Pass	Refer to figures
3	The standard deviation of load error at steady state over a 900 second period must not exceed 2.5% of the maximum contracted active power.	Pass	Standard deviation is assessed from 10 seconds until 900 seconds after the frequency step.
4	Provide an active power response consistent with the contracted performance within Primary, Secondary and/or High frequency response timescales.	Pass	Figure should show the active power response 'following' frequency as expected.  Include a plot where the frequency axis has been reversed and both vertical axes (response and frequency) have been scaled to be consistent with the contract table. Without considering delays, both plots should match and any anomalies can be observed and further investigated/explained.
	Overall Test Result	PASS	

### **Test Result Graphs**

Plot frequency injection and active power response vs time for each test.

Figure 1 – (to be added)



### Independent Technical Expert (ITE) Details

Company name

Primary contact name

Contact number /s

Email address

#### I / We confirm that I / We the following:

- (a) I/We am a/are Independent Technical Expert(s) (as defined in Appendix A of the NGESO's prevailing Testing Guidelines);
- (b) I/We have carried out an assessment of the [asset] described above in accordance with the testing guidelines set out in the Testing Guidelines;
- (c) the above details are, to my/our best knowledge and belief, true, accurate, complete and not misleading; and
- (d) the CV attached of my/our experience is to my/our best knowledge and belief, true, accurate, complete and not misleading.

Signed:

Date:



